

## 23.20. Server troubleshooting

### Service not running

If the client is unable to connect to the server, it is quite possible that the mSupply Server Service is not running.

You can check by going into Control Panel>Administrative Tools>Services



Look for the service named 4D. The status should be “running” or “started” and it should be set to automatic.



If it is not running or started you can click the play button above the list of services while you have 4D highlighted. The status should now read “running” or “Started”. If it doesn't please contact mSupply Support for help. [support@msupply.org.nz](mailto:support@msupply.org.nz)

### mSupply Client software can not see the mSupply Server?


Refer [mSupply Client software can not see the mSupply Server?](#)

### Sync not working

If, on a sync satellite client, the number of sync records stays static, or continues to grow over a significant period (hours), then sync between the (Sync Satellite server to the sync Primary server) has stalled.



A probable reason for this is that the Sync Satellite server can not connect to the sync Primary server. You can check this by checking the logs (**Special > View log...**):



Show Log...

Export Print Order by Find From 10/07/2018 To 10/07/2018 Today All

| Date       | Time     | User | Type          | Event                                                   | Source Table | Record Number |
|------------|----------|------|---------------|---------------------------------------------------------|--------------|---------------|
| 10/07/2018 | 18:34:01 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 18:40:22 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 18:40:43 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 18:47:04 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 18:47:26 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 18:53:47 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 18:54:09 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:00:31 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:00:52 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:07:13 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:07:34 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:13:55 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:14:17 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:20:38 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:20:59 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:27:20 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:27:42 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:34:04 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:34:25 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:40:46 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:41:08 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:47:29 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:47:50 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |
| 10/07/2018 | 19:54:11 |      | sync_incoming | Unable to access server in sync_get_remote_queue_siz... | 0            |               |
| 10/07/2018 | 19:54:33 |      | sync_outgoing | Unable to access server in sync_update_remote_record... | 0            |               |

OK

There are a number of possible reasons for this:

- The Sync Primary server hardware is down. Check that the Sync Primary server hardware is up.
- The Sync Primary service (software) is down. Check that the Sync Primary service (software) on the Sync Primary server hardware is up.
- The IP address of the Sync Primary server hardware is incorrect. The IP address of the Sync Primary server should be a domain name, e.g. `orgname.msupply.org`. However, this domain name will be mapped to an IP address that *should* be static. If the ip address of the Sync Primary is different to what the domain name server maps it to, then sync will fail. To confirm this:
  - Find the IP address of the Sync Primary server hardware, at the Command Prompt on the Sync Primary server, enter `ipconfig`.
  - Find the IP address that the domain name server thinks is associated with the domain name, at the Command Prompt on the Sync Satellite server, enter `nslookup orgname.msupply.org`. Compare the reported ip addresses.
- Access to the Sync Primary server hardware may be blocked by a firewall or proxy server on the Sync Satellite server network. A simple diagnostic test for this is to open a browser and enter the following in to the address field: <https://myserver.msupply.org/sync/>.
  - If the web page responds with an error message from the Primary Server, then the Primary Server is reachable:

← → ↻ Secure | <https://myserver.msupply.org/sync/>

```
{"lines":[{"description":"Invalid sync resource version specified"},"error":"Invalid sync resource version specified"}
```

- If the web page responds with a firewall or proxy error message, then the firewall / proxy server needs to be configured to allow access from the Primary secondary server to <https://myserver.msupply.org/sync/>:

// Previous: [25.19. The system log](#) | Next: [25.21. Help menu](#) //

From:

<https://docs.msupply.org.nz/> - mSupply documentation wiki

Permanent link:

[https://docs.msupply.org.nz/admin:server\\_troubleshooting?rev=1606824367](https://docs.msupply.org.nz/admin:server_troubleshooting?rev=1606824367)

Last update: **2020/12/01 12:06**

